



<b>Form C: Type Test Verification Report</b>			
<p>Type Approval and <b>Manufacturer</b> declaration of compliance with the requirements of G98.</p> <p>This form should be used when making a Type Test submission to the Energy Networks Association (ENA).</p> <p>If the <b>Micro-generator</b> is <b>Fully Type Tested</b> and already registered with the ENA <b>Type Test Verification Report</b> Register, the <b>Installation Document</b> should include the <b>Manufacturer's</b> Reference Number (the Product ID), and this form does not need to be submitted.</p> <p>Where the <b>Micro-generator</b> is not registered with the ENA <b>Type Test Verification Report</b> Register this form needs to be completed and provided to the <b>DNO</b>, to confirm that the <b>Micro-generator</b> has been tested to satisfy the requirements of this EREC G98.</p>			
<b>Manufacturer's</b> reference number		ERD-CR202101010	
<b>Micro-generator</b> technology		RHI-3P5K-HVES-5G, RHI-3P6K-HVES-5G, RHI-3P8K-HVES-5G, RHI-3P10K-HVES-5G	
<b>Manufacturer</b> name		Ginlong Technologies Co., Ltd.	
Address		No. 57 Jintong Road, Seafront (Binhai) IndustrialPark, Xiangshan, Ningbo, Zhejiang, 315712,P.R.China	
Tel	(+86)5746580 3377	Fax	(+86)574 6578 1606
E-mail	jiaqi.cao@ginlong.com	Web site	www.ginlong.com
<b>Registered Capacity</b> , use separate sheet if more than one connection option.	Connection Option		
	-	kW single phase, single, split or three phase system	
	5,6,8,10	kW three phase	
	-	kW two phases in three phase system	
	-	kW two phases split phase system	
<p><b>Manufacturer Type Test</b> declaration. - I certify that all products supplied by the company with the above <b>Type Tested</b> reference number will be manufactured and tested to ensure that they perform as stated in this document, prior to shipment to site and that no site modifications are required to ensure that the product meets all the requirements of EREC G98.</p>			
Signed	<i>Cao jiaqi</i> 27 Jan. 2021	On behalf of Manufacturer stamp	Ginlong Technologies 锦浪科技股份有限公司 GINLONG TECHNOLOGIES CO.,LTD.
<p>Note that testing can be done by the <b>Manufacturer</b> of an individual component or by an external test house.</p>			



<p>Where parts of the testing are carried out by persons or organisations other than the <b>Manufacturer</b> then that person or organisation shall keep copies of all test records and results supplied to them to verify that the testing has been carried out by people with sufficient technical competency to carry out the tests.</p>			
<p><b>Operating Range:</b> This test should be carried out as specified in EN 50438 D.3.1.</p> <p><b>Active Power</b> shall be recorded every second. The tests will verify that the <b>Micro-generator</b> can operate within the required ranges for the specified period of time.</p> <p>The <b>Interface Protection</b> shall be disabled during the tests.</p> <p>In case of a PV <b>Micro-generator</b> the PV primary source may be replaced by a <b>DC</b> source.</p> <p>In case of a full converter <b>Micro-generator</b>(eg wind) the primary source and the prime mover <b>Inverter/rectifier</b> may be replaced by a <b>DC</b> source.</p> <p>In case of a DFIG <b>Micro-generator</b> the mechanical drive system may be replaced by a test bench motor.</p>			
<p>Test 1</p> <p>Voltage = 85% of nominal (195.5 V)</p> <p>Frequency = 47.5 Hz</p> <p>Power factor = 1</p> <p>Period of test 90 minutes</p>		<p>Tested with the specified conditions, in the 90 minutes period of time, the inverters operate normally</p>	
<p>Test 2</p> <p>Voltage = 110% of nominal (253 V).</p> <p>Frequency = 51.5 Hz</p> <p>Power factor = 1</p> <p>Period of test 90 minutes</p>		<p>Tested with the specified conditions, in the 90 minutes period of time, the inverters operate normally</p>	
<p>Test 3</p> <p>Voltage = 110% of nominal (253 V).</p> <p>Frequency = 52.0 Hz</p> <p>Power factor = 1</p> <p>Period of test 15 minutes</p>		<p>Tested with the specified conditions, in the 15 minutes period of time, the inverters operate normally</p>	
<p>Power Quality – Harmonics: These tests should be carried out as specified in BS EN 61000-3-2. The chosen test should be undertaken with a fixed source of energy at two power levels a) between 45 and 55% and b) at 100% of Registered Capacity. The test requirements are specified in Annex A1A.1.3.1 (Inverter connected) or Annex A2 A.2.3.1 (Synchronous).</p>			
<p>Micro-generator tested to BS EN 61000-3-2</p>			
<p><b>Micro-generator</b> rating per phase (rpp)</p>		<p>3.333</p>	<p>kW</p>
<p>Harmonic</p>	<p>At 45-55% of <b>Registered Capacity</b></p>	<p>100% of <b>Registered Capacity</b></p>	
<p><math>NV = MV * 3.68 / rpp</math></p>			



L1	Measured Value MV in Amps	NV	Measured Value MV in Amps	NV	Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2	0.040	0.044	0.063	0.070	1.080	
3	0.022	0.024	0.028	0.030	2.300	
4	0.028	0.031	0.041	0.045	0.430	
5	0.040	0.044	0.050	0.055	1.140	
6	0.021	0.023	0.030	0.033	0.300	
7	0.062	0.069	0.079	0.087	0.770	
8	0.025	0.027	0.034	0.038	0.230	
9	0.028	0.030	0.035	0.039	0.400	
10	0.021	0.023	0.025	0.028	0.184	
11	0.017	0.018	0.025	0.028	0.330	
12	0.018	0.020	0.023	0.026	0.153	
13	0.036	0.040	0.049	0.054	0.210	
14	0.016	0.018	0.023	0.025	0.131	
15	0.015	0.016	0.016	0.018	0.150	
16	0.010	0.011	0.008	0.009	0.115	
17	0.013	0.014	0.014	0.015	0.132	
18	0.013	0.014	0.014	0.015	0.102	
19	0.026	0.028	0.050	0.055	0.118	
20	0.010	0.011	0.009	0.010	0.092	
21	0.010	0.011	0.008	0.009	0.107	0.160
22	0.007	0.008	0.011	0.012	0.084	
23	0.021	0.023	0.022	0.024	0.098	0.147
24	0.009	0.010	0.011	0.012	0.077	



25	0.025	0.028	0.054	0.060	0.090	0.135
26	0.007	0.008	0.013	0.014	0.071	
27	0.009	0.010	0.012	0.014	0.083	0.124
28	0.008	0.009	0.011	0.012	0.066	
29	0.018	0.020	0.016	0.018	0.078	0.117
30	0.008	0.009	0.012	0.013	0.061	
31	0.020	0.022	0.040	0.045	0.073	0.109
32	0.007	0.008	0.012	0.014	0.058	
33	0.010	0.011	0.011	0.012	0.068	0.102
34	0.008	0.009	0.009	0.010	0.054	
35	0.013	0.015	0.014	0.015	0.064	0.096
36	0.008	0.009	0.010	0.011	0.051	
37	0.015	0.017	0.029	0.032	0.061	0.091
38	0.008	0.008	0.010	0.011	0.048	
39	0.008	0.009	0.009	0.010	0.058	0.087
40	0.008	0.008	0.009	0.010	0.046	
<b>L2</b>	Measured Value MV in Amps	NV	Measured Value MV in Amps	NV	Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2	0.015	0.017	0.013	0.014	1.080	
3	0.031	0.034	0.043	0.047	2.300	
4	0.033	0.036	0.055	0.061	0.430	
5	0.071	0.078	0.099	0.110	1.140	
6	0.028	0.031	0.045	0.050	0.300	
7	0.097	0.107	0.138	0.152	0.770	
8	0.026	0.029	0.042	0.046	0.230	



9	0.038	0.042	0.055	0.061	0.400	
10	0.031	0.034	0.049	0.054	0.184	
11	0.029	0.032	0.046	0.051	0.330	
12	0.023	0.025	0.035	0.038	0.153	
13	0.050	0.055	0.071	0.078	0.210	
14	0.017	0.019	0.023	0.026	0.131	
15	0.019	0.021	0.026	0.029	0.150	
16	0.017	0.018	0.026	0.029	0.115	
17	0.022	0.025	0.026	0.029	0.132	
18	0.015	0.017	0.021	0.023	0.102	
19	0.030	0.033	0.051	0.056	0.118	
20	0.009	0.010	0.009	0.009	0.092	
21	0.014	0.015	0.015	0.017	0.107	0.160
22	0.009	0.009	0.014	0.016	0.084	
23	0.028	0.031	0.026	0.029	0.098	0.147
24	0.008	0.009	0.009	0.010	0.077	
25	0.027	0.029	0.054	0.060	0.090	0.135
26	0.007	0.008	0.016	0.017	0.071	
27	0.008	0.008	0.009	0.009	0.083	0.124
28	0.013	0.014	0.019	0.021	0.066	
29	0.018	0.019	0.015	0.016	0.078	0.117
30	0.007	0.008	0.011	0.012	0.061	
31	0.025	0.027	0.044	0.049	0.073	0.109
32	0.008	0.009	0.014	0.015	0.058	



33	0.008	0.009	0.009	0.010	0.068	0.102
34	0.011	0.013	0.013	0.014	0.054	
35	0.012	0.013	0.015	0.017	0.064	0.096
36	0.008	0.009	0.010	0.011	0.051	
37	0.018	0.020	0.029	0.032	0.061	0.091
38	0.008	0.009	0.010	0.011	0.048	
39	0.007	0.008	0.008	0.009	0.058	0.087
40	0.009	0.010	0.010	0.011	0.046	
<b>L3</b>	Measured Value MV in Amps	NV	Measured Value MV in Amps	NV	Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2	0.035	0.038	0.059	0.065	1.080	
3	0.018	0.020	0.018	0.020	2.300	
4	0.012	0.013	0.019	0.021	0.430	
5	0.073	0.080	0.097	0.107	1.140	
6	0.012	0.013	0.018	0.019	0.300	
7	0.071	0.078	0.109	0.120	0.770	
8	0.008	0.009	0.011	0.012	0.230	
9	0.018	0.019	0.024	0.027	0.400	
10	0.015	0.017	0.026	0.029	0.184	
11	0.028	0.031	0.032	0.036	0.330	
12	0.011	0.013	0.017	0.018	0.153	
13	0.046	0.051	0.075	0.083	0.210	
14	0.008	0.009	0.009	0.009	0.131	
15	0.014	0.016	0.018	0.020	0.150	
16	0.010	0.011	0.021	0.024	0.115	



17	0.024	0.027	0.019	0.021	0.132	
18	0.009	0.010	0.012	0.013	0.102	
19	0.034	0.037	0.064	0.070	0.118	
20	0.010	0.011	0.012	0.013	0.092	
21	0.015	0.017	0.017	0.019	0.107	0.160
22	0.009	0.009	0.017	0.018	0.084	
23	0.024	0.026	0.019	0.021	0.098	0.147
24	0.008	0.009	0.009	0.010	0.077	
25	0.026	0.029	0.059	0.065	0.090	0.135
26	0.008	0.009	0.013	0.015	0.071	
27	0.010	0.011	0.012	0.013	0.083	0.124
28	0.010	0.011	0.018	0.020	0.066	
29	0.016	0.018	0.018	0.020	0.078	0.117
30	0.008	0.009	0.009	0.009	0.061	
31	0.025	0.028	0.050	0.056	0.073	0.109
32	0.007	0.008	0.010	0.011	0.058	
33	0.009	0.009	0.013	0.014	0.068	0.102
34	0.010	0.011	0.015	0.017	0.054	
35	0.014	0.015	0.017	0.019	0.064	0.096
36	0.007	0.008	0.009	0.010	0.051	
37	0.021	0.024	0.035	0.039	0.061	0.091
38	0.008	0.009	0.010	0.011	0.048	
39	0.010	0.011	0.013	0.014	0.058	0.087
40	0.010	0.011	0.011	0.012	0.046	



Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

**Power Quality – Voltage fluctuations and Flicker:** These tests should be undertaken in accordance with EREC G98 Annex A1 A.1.3.3 (Inverter connected) or Annex A2 A.2.3.3 (Synchronous).

	Starting			Stopping			Running	
L1	d max	d c	d(t)	d max	d c	d(t)	P <sub>st</sub>	P <sub>lt</sub> 2 hours
Measured Values at test impedance	0.402	0.311	0	0.352	0	0	0.048	0.069
Normalised to standard impedance	0.402	0.311	0	0.352	0	0	0.048	0.069
Normalised to required maximum impedance	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Limits set under BS EN 61000-3-11	4%	3.3%	3.3%	4%	3.3%	3.3%	1.0	0.65
	Starting			Stopping			Running	
L2	d max	d c	d(t)	d max	d c	d(t)	P <sub>st</sub>	P <sub>lt</sub> 2 hours
Measured Values at test impedance	0.421	0.334	0	0.384	0	0	0.051	0.071
Normalised to standard impedance	0.421	0.334	0	0.384	0	0	0.051	0.071
Normalised to required maximum impedance	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Limits set under BS EN 61000-3-11	4%	3.3%	3.3%	4%	3.3%	3.3%	1.0	0.65





	Starting			Stopping			Running	
<b>L3</b>	d max	d c	d(t)	d max	d c	d(t)	P <sub>st</sub>	P <sub>It</sub> 2 hours
Measured Values at test impedance	0.435	0.357	0	0.429	0	0	0.054	0.075
Normalised to standard impedance	0.435	0.357	0	0.429	0	0	0.054	0.075
Normalised to required maximum impedance	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Limits set under BS EN 61000-3-11	4%	3.3%	3.3%	4%	3.3%	3.3%	1.0	0.65
Test Impedance	R	0.24	Ω	X	0.15	Ω		
Standard Impedance	R	0.24 * 0.4 ^	Ω	X	0.15 * 0.25 ^	Ω		
Maximum Impedance	R	N/A	Ω	X	N/A	Ω		

Applies to three phase and split single phase **Micro-generators**.

^ Applies to single phase **Micro-generators** and **Micro-generators** using two phases on a three phase system.

For voltage change and flicker measurements the following formula is to be used to convert the measured values to the normalised values where the power factor of the generation output is 0.98 or above.

Normalised value = Measured value\*reference source resistance/measured source resistance at test point.

Single phase units reference source resistance is 0.4 Ω

Two phase units in a three phase system reference source resistance is 0.4 Ω.

Two phase units in a split phase system reference source resistance is 0.24 Ω.

Three phase units reference source resistance is 0.24 Ω.

Where the power factor of the output is under 0.98 then the X to R ratio of the test impedance should be close to that of the Standard Impedance.

The stopping test should be a trip from full load operation.

The duration of these tests need to conform to the particular requirements set out in the testing notes for the technology under test. Dates and location of the test need to be noted below.				
Test start date	09.Dec.2020	Test end date	10.Dec.2020	
Test location	Ginlong electrical R&D LAB			
<b>Power quality – DC injection:</b> This test should be carried out in accordance with EN 50438 Annex D.3.10				
Test Power level	20%	50%	75%	100%
Recorded value in Amps of L1	11.9mA	23.5mA	30.8mA	30.3mA
As % of rated AC current	0.082%	0.163%	0.213%	0.210%
Recorded value in Amps of L2	27.3mA	23.8mA	26.7mA	28.2mA
As % of rated AC current	0.189%	0.165%	0.185%	0.195%
Recorded value in Amps of L3	28.3mA	26.4mA	25.3mA	26 mA
As % of rated AC current	0.196%	0.183%	0.175%	0.180%
Limit	0.25%	0.25%	0.25%	0.25%
<b>Power Quality – Power factor:</b> This test shall be carried out in accordance with EN 50538 Annex D.3.4.1 but with nominal voltage -6% and +10%. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test.				
Test Voltage vaule	216.2 V	230 V	253 V	
Phase	L1/L2/L3	L1/L2/L3	L1/L2/L3	
20% of Registered Capacity	0.977/0.978/0.964	0.972/0.972/0.956	0.962/0.964/0.961	
50% of Registered Capacity	0.996/0.996/0.993	0.995/0.995/0.991	0.993/0.993/0.987	
75% of Registered Capacity	0.998/0.998/0.996	0.997/0.998/0.995	0.996/0.997/0.994	
100% of Registered Capacity	0.998/0.998/0.996	0.998/0.998/0.996	0.998/0.998/0.996	
Limit	>0.95	>0.95	>0.95	
<b>Protection – Frequency tests:</b> These tests should be carried out in accordance with EN 50438 Annex D.2.4 and the notes in EREC G98 Annex A1 A.1.2.3 ( <b>Inverter</b> connected) or Annex A2 A.2.2.3 (Synchronous)				



Function	Setting		Trip test		"No trip tests"	
	Frequency	Time delay	Frequency	Time delay	Frequency /time	Confirm no trip
U/F stage 1	47.5 Hz	20 s	47.49 Hz	20.050s	47.7 Hz 30 s	Yes
U/F stage 2	47 Hz	0.5 s	46.99 Hz	0.516s	47.2 Hz 19.5 s	Yes
					46.8 Hz 0.45 s	Yes
O/F stage 1	52 Hz	0.5 s	52.03 Hz	0.513s	51.8 Hz 120 s	Yes
					52.2 Hz 0.45 s	Yes

Note. For frequency trip tests the frequency required to trip is the setting  $\pm 0.1$  Hz. In order to measure the time delay a larger deviation than the minimum required to operate the protection can be used. The "No trip tests" need to be carried out at the setting  $\pm 0.2$  Hz and for the relevant times as shown in the table above to ensure that the protection will not trip in error.

**Protection – Voltage tests:** These tests should be carried out in accordance with EN 50438 Annex D.2.3 and the notes in EREC G98 Annex A1 A.1.2.2 (**Inverter** connected) or Annex A2 A.2.2.2 (Synchronous)

Function	Setting		Trip test		"No trip tests"	
	Voltage	Time delay	Voltage	Time delay	Voltage /time	Confirm no trip
U/V						
L1-N	184 V	2.5 s	183.4V	2.512s	188V 5.0 s	Yes
L2-N			183.6V	2.526s	188V 5.0 s	Yes
L3-N			184.2V	2.510s	188V 5.0 s	Yes
					180 V 2.45 s	Yes
O/V stage 1	Setting		Trip test		"No trip tests"	
L1-N	262.2 V	1.0 s	261.9V	1.015s	258.2 V 5.0 s	Yes
L2-N			262.5V	1.018s	258.2 V 5.0 s	Yes



L3-N			262.8V	1.021s	258.2 V 5.0 s	Yes
O/V stage 2	Setting		Trip test		"No trip tests"	
L1-N	273.7 V	0.5 s	273.0V	0.532s	269.7V 0.95 s	Yes
L2-N			273.5V	0.527s	269.7V 0.95 s	Yes
L3-N			273.6V	0.530s	269.7V 0.95 s	Yes
					277.7V 0.45 s	Yes

Note for Voltage tests the Voltage required to trip is the setting  $\pm 3.45$  V. The time delay can be measured at a larger deviation than the minimum required to operate the protection. The No trip tests need to be carried out at the setting  $\pm 4$  V and for the relevant times as shown in the table above to ensure that the protection will not trip in error.

Protection – Loss of Mains test: For PV Inverters shall be tested in accordance with BS EN 62116. Other Inverters should be tested in accordance with EN 50438 Annex D.2.5 at 10%, 55% and 100% of rated power.

To be carried out at three output power levels with a tolerance of plus or minus 5% in Test Power levels.

Test Power	10%	55%	100%	10%	55%	100%
Balancing load on islanded network	95% of Registered Capacity	95% of Registered Capacity	95% of Registered Capacity	105% of Registered Capacity	105% of Registered Capacity	105% of Registered Capacity
Trip time. Limit is 0.5 s						

For Multi phase **Micro-generators** confirm that the device shuts down correctly after the removal of a single fuse as well as operation of all phases.

Test Power	10%	55%	100%	10%	55%	100%
Balancing load on islanded network	95% of Registered Capacity	95% of Registered Capacity	95% of Registered Capacity	105% of Registered Capacity	105% of Registered Capacity	105% of Registered Capacity
Trip time. Ph1 fuse removed						
Test Power	10%	55%	100%	10%	55%	100%



Balancing load on islanded network	95% of Registered Capacity	95% of Registered Capacity	95% of Registered Capacity	105% of Registered Capacity	105% of Registered Capacity	105% of Registered Capacity
Trip time. Ph2 fuse removed						
Test Power	10%	55%	100%	10%	55%	100%
Balancing load on islanded network	95% of Registered Capacity	95% of Registered Capacity	95% of Registered Capacity	105% of Registered Capacity	105% of Registered Capacity	105% of Registered Capacity
Trip time. Ph3 fuse removed						
Note for technologies which have a substantial shut down time this can be added to the 0.5 s in establishing that the trip occurred in less than 0.5 s. Maximum shut down time could therefore be up to 1.0 s for these technologies.						
Indicate additional shut down time included in above results.					--	
For <b>Inverters</b> tested to BS EN 62116 the following sub set of tests should be recorded in the following table.						
Test Power and imbalance	33%-5% Q Test 22	66%-5% Q Test 12	100%-5% P Test 5	33%+5% Q Test 31	66%+5% Q Test 21	100%+5% P Test 10
Trip time. Limit is 0.5 s	0.312s	0.331s	0.328s	0.295s	0.306s	0.339s
<b>Protection – Frequency change, Vector Shift Stability test:</b> This test should be carried out in accordance with EREC G98 Annex A1 A.1.2.6 ( <b>Inverter</b> connected) or Annex A2 A.2.2.6 (Synchronous).						
	Start Frequency	Change	Confirm no trip			
Positive Vector Shift	49.0 Hz	+50 degrees	Yes			
Negative Vector Shift	50.0 Hz	- 50 degrees	Yes			
<b>Protection – Frequency change, RoCoF Stability test:</b> The requirement is specified in section 11.3, test procedure in Annex A.1.2.6( <b>Inverter</b> connected) or Annex A2 A.2.2.6 (Synchronous).						
Ramp range	Test frequency ramp:	Test Duration	Confirm no trip			
49.0 Hz to 51.0 Hz	+0.95 Hzs <sup>-1</sup>	2.1 s	Yes			
51.0 Hz to 49.0 Hz	-0.95 Hzs <sup>-1</sup>	2.1 s	Yes			
<b>Limited Frequency Sensitive Mode – Overfrequency test:</b> This test should be carried out in accordance with EN 50438 Annex D.3.3 Power response to over- frequency. The test should be carried out using the specific threshold frequency of 50.4 Hz and <b>Droop</b> of10%.						



Test sequence at <b>Registered Capacity</b> >80%	Measured <b>Active Power</b> Output	Frequency	Primary Power Source	<b>Active Power</b> Gradient
Step a) 50.00 Hz ±0.01 Hz	10015	50.00Hz	10500	-
Step b) 50.45 Hz ±0.05 Hz	9908	50.45Hz		-
Step c) 50.70 Hz ±0.10 Hz	9376	50.70Hz		-
Step d) 51.15 Hz ±0.05 Hz	8476	51.15Hz		-
Step e) 50.70 Hz ±0.10 Hz	9368	50.70Hz		-
Step f) 50.45 Hz ±0.05 Hz	9910	50.45Hz		-
Step g) 50.00 Hz ±0.01 Hz	9970	50.00Hz		60kW/min
Test sequence at <b>Registered Capacity</b> 40% - 60%	Measured <b>Active Power</b> Output	Frequency	Primary Power Source	<b>Active Power</b> Gradient
Step a) 50.00 Hz ±0.01 Hz	5007	50.00Hz	5500	-
Step b) 50.45 Hz ±0.05 Hz	4960	50.45Hz		-
Step c) 50.70 Hz ±0.10 Hz	4709	50.70Hz		-
Step d) 51.15 Hz ±0.05 Hz	4258	51.15Hz		-
Step e) 50.70 Hz ±0.10 Hz	4708	50.70Hz		-
Step f) 50.45 Hz ±0.05 Hz	4960	50.45Hz		-
Step g) 50.00 Hz ±0.01 Hz	5007	50.00Hz		60kW/min
Steps as defined in EN 50438				
<b>Power output with falling frequency test:</b> This test should be carried out in accordance with EN 50438 Annex D.3.2 active power feed-in at under-frequency.				
Test sequence	Measured <b>Active Power</b> Output	Frequency	Primary power source	
Test a) 50 Hz ± 0.01 Hz	10010	50.00Hz	10482	
Test b) Point between 49.5 Hz and 49.6 Hz	10015	49.55Hz	10490	
Test c) Point between 47.5 Hz and 47.6 Hz	9994	47.55Hz	10478	



NOTE: The operating point in Test (b) and (c) shall be maintained for at least 5 minutes						
<b>Re-connection timer.</b>						
Test should prove that the reconnection sequence starts after a minimum delay of 20 s for restoration of voltage and frequency to within the stage 1 settings of Table 2.						
Time delay setting	Measured delay		Checks on no reconnection when voltage or frequency is brought to just outside stage 1 limits of table 2.			
30s	35.6s		At 266.2 V	At 180 V	At 47.4 Hz	At 52.1 Hz
Confirmation that the <b>Micro-generator</b> does not re-connect.			Yes	Yes	Yes	Yes
<b>Fault level contribution:</b> These tests shall be carried out in accordance with EREC G98 Annex A1 A.1.3.5 ( <b>Inverter</b> connected) and Annex A2 A.2.3.4 (Synchronous).						
For machines with electro-magnetic output				For <b>Inverter</b> output		
Parameter	Symbol	Value	Time after fault	Volts	Amps	
Peak Short Circuit current	$i_p$	--	20 ms	54.5V	18.53A	
Initial Value of aperiodic current	$A$	--	100 ms	52.9V	0	
Initial symmetrical short-circuit current*	$I_k$	--	250 ms	51.9V	0	
Decaying (aperiodic) component of short circuit current*	$i_{DC}$	--	500 ms	52.7V	0	
Reactance/Resistance Ratio of source*	$X/R$	--	Time to trip	0.072s	In seconds	
For rotating machines and linear piston machines the test should produce a 0 s – 2 s plot of the short circuit current as seen at the <b>Micro-generator</b> terminals.						
* Values for these parameters should be provided where the short circuit duration is sufficiently long to enable interpolation of the plot						
<b>Logic Interface.</b>					Yes	
<b>Self-Monitoring solid state switching:</b> No specified test requirements. Refer to EREC G98 Annex A1 A.1.3.6 ( <b>Inverter</b> connected).					NA	
It has been verified that in the event of the solid state switching device failing to disconnect the <b>Micro-generator</b> , the voltage on the output					N/A (Solid state switch means electronic switch, Solis inverter uses mechanical dual relay protection with relay checks,	



side of the switching device is reduced to a value below 50 V within 0.5 s.	which drops the voltage below 50V in 0.5s)
Additional comments	
All the tests above were conducted on Inverter model RHI-3P10K-HVES-5G. Inverter models RHI-3P5K-HVES-5G, RHI-3P6K-HVES-5G, RHI-3P8K-HVES-5G have the same hardware and software with model RHI-3P10K-HVES-5G. The test results can be referred .	